





**DIESEL GENERATING SET**

**YOUR TRUSTED GENSET COMPANY**



SPECIFICATION GENSET	OPEN TYPE	SILENT TYPE
<b>Model Genset</b>	PL 80 P	PL 80 P
<b>Power Output</b>	80 Kva / 64 Kw	80 Kva / 64 Kw
<b>Phase</b>	3 (three)	3 (three)
<b>Frequency</b>	50 Hz @ 1500RPM	50 Hz @1500 RPM
<b>Voltage</b>	220/380V	220/380V
<b>Control Panel</b>	Deep Sea Module, Pilot Lamp Indicator, Emergency Stop Button, MCCB	Deep Sea Module, Pilot Lamp Indicator, Emergency Stop Button, MCCB
<b>Accessories</b>	Fuel Tank, Residential Muffler, Batteries, Tools Kit	Fuel Tank, Residential Muffler, Batteries, Tools Kit
<b>Dimension LxWxT</b>	2000 x 900 x 1900mm	2600 x 1000 x 1300mm
<b>Weight</b>	1103 kg	1524 kg
<b>Fuel Tank Cap (Ltr)</b>	140	100

ENGINE	
<b>Type</b>	1104A-44TG2
<b>Cooling System</b>	Water Cooled with Radiator
<b>Number of cylinders</b>	4 vertical in-line
<b>Cycle</b>	4 stroke
<b>Bore x Stroke</b>	105 x 127mm
<b>Displacement</b>	4.400 liters
<b>Total Lubrication cap</b>	8.0 liters
<b>Fuel Consumption (L/H)</b>	14 (75% Load) / 18.7 (100% Load)

GENERATOR	
<b>Insulation System</b>	Class H
<b>Protection</b>	IP 23
<b>Rated Power Factor</b>	0.8
<b>Stator Winding</b>	Double Layer Laps
<b>Winding Pitch</b>	Two Thirds
<b>Winding Leads</b>	12

Hubungi kontak dibawah untuk harga dan diskon terbaik :

**PT. DUCOTTI DIESELINDO PERSADA**  
 Pergudangan EHA, Jl Raya Legok KM.06 No.77  
 Desa Carangpulang Tangerang, Indonesia.  
 021 2222 7058  
 info@powerline.co.id



www.powerline.co.id  
 www.perkinsgenset.co.id  
 www.servicegensetpowerline.com